

Pro-EM Controller

Emergency Lighting Controller



Product Overview

Specifications

Input	190 ~ 250V/AC 50/60Hz
Adjustable Output	12 ~ 50V/DC
Battery Back-up	3 hours
Temperature control	70°C
Uout	50V
Battery Voltage (NiMH)	4.8V NiMH
Battery capacity (Ah)	2.5Ah
Teach Button	- Silux Control® network - Software teach available
Network	Silux Control® RF proprietary encrypted with long range monitoring and full meshing capabilities
RF Range	100m open air & meshing up to 1km
Radio Frequency	868MHZ (Adjustable frequency to meet different country legislations)
Encryption	Silux Control® RF proprietary meshing
Language	English, others coming soon
OS	Android 4.0+, iOS 8.0+, Windows 7+
App Software	Silux Control® can be integrated with other automation features of Silux Control®

Ensure your emergency lighting is kept at the healthiest status level without requiring human assistance or interventions. Remote access from anywhere in the world via the Silux Control® app software.

Features:

- Hourly updates sent to the IntelliHub® such as battery condition and status, lighting condition and status, battery condition under 3 hour test operation
- Automatically capable of doing weekly, monthly and yearly tests autonomously
- Set time and day you require these tests to automatically take place
- Create logs and reports on status and events occurring on test
- Keeps hourly logs of general status of all devices and battery

